



安定器容量表


型式	対応ランプ			入力電圧	周波数	サイズ	サイズ	入力電流		入力電力				
	ランプ型式	W数	灯数					100/200/242V	100/200/242V					
インバータ式														
EWK型 (屋外用)	FL・FLR・FHF	40W	1	フリー	フリー	屋外		屋内						
			2			430×51×32	360×40×25	0.30/0.15/0.13A	29/29/29W					
	FL	32W	1			430×51×32	360×40×25	0.61/0.30/0.26A	61/60/60W					
			2			430×51×32	360×40×25	0.30/0.15/0.13A	30/30/30W					
EK型 (屋内用)	FL・FLR	20W	1			430×51×32	360×40×25	0.57/0.28/0.23A	56/55/55W					
			2			430×51×32	360×40×25	0.18/0.09/0.08A	18/18/18W					
										0.34/0.17/0.14A		32/32/32W		

型式	対応ランプ			入力電圧	周波数	サイズ	入力電流		入力電力		高効率用 コンデンサ						
	ランプ型式	W数	灯数				低効率	高効率	低効率	高効率							
グロー式																	
FH型	FL	52W	1	100V	50Hz	165×62×47	1.27A	0.76A	65W	65W	22 μ F						
			1		60Hz	165×62×47					18 μ F						
			40W		1	50Hz					150×52×40	0.90A	0.53A	49W	48W	17 μ F	
					1	60Hz					150×52×40					14 μ F	
			32W		1	50Hz					150×52×40	0.66A	0.41A	39W	39W	14 μ F	
					1	60Hz					150×52×40					11 μ F	
		30W	1		50Hz	122×47×34	0.61A	0.40A	37W	37W	9 μ F						
			1		60Hz	122×47×34					7 μ F						
		20W	1		50Hz	100×42×32	0.36A	0.27A	24W	24W	5.5 μ F						
			1		60Hz	100×42×32					4.5 μ F						
		15W	1		50Hz	100×42×32	0.30A	0.21A	18.9W	19W	5.5 μ F						
			1		60Hz	100×42×32					4.5 μ F						
		10W	1		50Hz	110×50×31	0.23A	0.14A	13W	13W	3.5 μ F						
			1		60Hz	110×50×31					3 μ F						
		200V	52W		1	50Hz	165×62×47	0.63A	0.36A	65W	65W	6 μ F					
					1	60Hz	165×62×47					5.5 μ F					
					40W	1	50Hz					130×53×39	0.42A	0.24A	49W	46W	4.5 μ F
						1	60Hz					130×53×39					3.5 μ F
					32W	1	50Hz					150×52×39	0.435A	0.22A	39W	40W	4.5 μ F
						1	60Hz					150×52×39					3.5 μ F
			30W		1	50Hz	150×52×40	0.61A	0.24A	44W	44W	7.5 μ F					
					1	60Hz	150×52×40					6 μ F					
			20W		1	50Hz	125×50×38	0.36A	0.15A	29W	29W	4.5 μ F					
					1	60Hz	125×50×38					3.5 μ F					
15W	1		50Hz	125×50×38	0.30A	0.13A	24W	24W	3.5 μ F								
	1		60Hz	125×50×38					3 μ F								
10W	1	50Hz	110×50×31	0.23A	0.10A	18W	18W	3.5 μ F									
	1	60Hz	110×50×31					3 μ F									
100V	15W	1	50Hz	77×48×28	0.30A	0.21A	19W	19W	5.5 μ F								
		1	60Hz	77×48×28					4.5 μ F								
		10W	1	50Hz					76×45×26	0.23A	0.14A	13W	13W	3.5 μ F			
			1	60Hz					76×45×26					3 μ F			
		8W	1	50Hz					76×45×26	0.17A	—	11W	—	—			
			1	60Hz					76×45×26					—			
	6W	1	50Hz	76×45×26	0.147A	—	9W	—	—								
		1	60Hz	76×45×26					—								
	4W	1	50Hz	76×45×26	0.162A	—	8.5W	—	—								
		1	60Hz	76×45×26					—								
	ラピッド式																
	RFD型	FLR	40W	1	100V	50Hz	230×58×43	—	0.45A	—	44W	—					
1				60Hz		230×58×43	—										
20W				1		50Hz	230×58×43					—	0.30A	—	29W	—	
				1		60Hz	230×58×43									—	
200V			40W	1	50Hz	230×58×43	—	0.24A	—	46W	—						
				1	60Hz	230×58×43					—						
			20W	1	50Hz	230×58×43					—	0.15A	—	29W	—		
				1	60Hz	230×58×43									—		


グロー式



ラピッド式



インバータ式1灯用



インバータ式2灯用

